


1st Test circuit for Meyra "Sprint" model: 1.592

This test circuit allows you to control the blackbox (motordrivers) without the joystick console

How to connect - step by step:

- Disconnect connector "X4" on main board
- Disconnect the thick red cable, which goes into the blackbox and connect it directly to +24V
- Connect the power supply (+24V , GND) of the test circuit board
- Adjust P1, P2, P3
- Disconnect power supply of test board
- Connect pin 2 - 5 of test board to the white plug at the end of the cable which comes out of the black box (X4)
- Connect the power supply (+24V , GND) of the test circuit board
- Now, you should be able to control the driving functions with P4 and P5



Connector on main board which goes to blackbox.
Pin 1 is reserved for error feedbacks.